

# FG- EVAC-MPS8Z \_AP MULTI-ZONE PAGING MICROPHONE



## PRODUCT OVERVIEW

The **FG-EVAC-MPS8Z** is a high performance digital paging station for the PA/VA system NEO.

Up to 8 **FG-EVAC-MPS8Z \_AP** paging microphones can be connected in a bus configuration to the ACSI bus of the NEO system via CAT5 cable.

The ACSI bus allows a maximum distance of 1Km and provides priority levels between the devices connected to the bus.

It has 8 buttons for paging to 8 zones and additional zone buttons can be added with **FG-EVAC-MPS8Z \_AP** units. It features an "all-call" button, busy line signal and auto-lock function.

The **FG-EVAC-MPS8Z \_AP** offers an Event button that combined with the zone buttons allow a wide variety of system's functions such as launching pre-recorded messages or loading presets.

The sound processing has been configured to achieve high quality results on the paging of voice, in terms of distortion, sensitivity, bandwidth and signal/noise ratio.

It has an iron chassis to provide a superior stability and protection against damages. All buttons are designed for an intensive use.

## Features

- 8-zone programmable buttons.
- Event activator.
- Recall function.
- Auto-lock function.
- LED indications for zone selection.
- LED indicators of the LDA NEO system's state (EMG, FLT or LINK).
- LED Indicators of busy and conceded word.
- Power directly from NEO thorough the UTP Cable and
- High performance durable microphone capsule.



Connected in a bus configuration

Rear and front view:



MODEL	DESCRIPTION
FG-EVAC-MPS8Z _AP	Multi-Zone Paging Microphone

## Technical Specification

Power supply :	5V dc, Type A/B MiniUSB connector
Power consumption :	1A
Frequency response :	200- 15000 Hz (+/-2dB).
Signal to noise ratio :	R> 98dB, A-weighted
Sensitivity	-43 dB. at 1KHz
Direccional axis	Axial with hipercardioid polar diagram response.
Kind of transducer	Condenser.
Indicators	State: Emergency, Failure, Link, Busy, Busy Line, Conceded Word. 8 indicators Zone selected. Gooseneck includes illuminated ring for conceded word.
Buttons	3 x programmable functions, 1 x recall, 1 x select / unselect all zones, 8 x zone selection, 1 x Talk
ACSI Bus	2 x Balanced Audio (In+Loop)1Vp, 0,707Vrms. 10 K $\Omega$ , 2 x RJ-45 Female, Total 800m. / 2624,7ft
Aux Mic Input	1 x Unbalanced input, 15mV, 47 K $\Omega$ , 1 x Minijack Mono 2,5mm
Dimensions without gooseneck (W x H x D)	95 x 65 x 190 mm / 3,75" x 2,56" x 7,48"
Gooseneck length	350mm / 13,78"
Operating Conditions	-5 °C to +45 °C / 23 °F to 113 °F 5% to 95% Relative Humidity (no condensation)
Finish	Fe, Grey RAL 7016
Weight :	0,93 Kg



“ Fireguard aims to be customer’s first choice to safeguard from hazardous fires, by designing, developing the latest technology products with high quality and reliability.”

### FIREGUARD GLOBAL LTD.

Tel: 00-44-8450751042

Fax: 00-44-8459751043

Email: Info@Fireguard-Uk.com

www.fireguard-Uk.com



Unit 11 · Chancel Industrial Estate · Newhall Street  
Willenhall · WV13 1NX · United Kingdom



FS546607

